

# Digital Milliohm Meter

## MO-5000

**HTC**<sup>TM</sup>  
**INSTRUMENTS**

### Features:

- Large LCD Display for easy reading
- 4 wire testing, capable of testing extreme low resistance
- Accurate measurement of conductor, electric heating elements and solder point
- HOLD key for data hold
- Connection for external power supply
- High measurement range of 0.01mΩ to 2kΩ at 6 ranges
- Backlight LCD for easy reading under dark light
- Strong anti-magnetic and anti-jamming functions
- Full function Protection



### Technical Data :

Range	Range	Resolution	Measuring Current
20mΩ	±(1.5%rdg±3)	0.01mΩ	Approx. 1000mA
200mΩ		0.1mΩ	
2Ω	±(0.5%rdg±3)	1mΩ	Approx. 500mA
20Ω		10mΩ	
200Ω		100mΩ	
2kΩ		1 Ω	

Special function	MO-5000
Low battery indication	Less than approx. 7.5V
Functional protection	✓
Sampling rate	3 times/sec.
Operation mode	Manual range
Max. display	1999
LCD size	75 x52 mm
Power Source	1.5V AA battery x6pcs, or external DC 9Vpower Source
Power consumption	Quiescent current approx.50mA

- **Standard Accessories:**4-wire test lead, shoulder strap, battery, operation Manual, Packing Gift box
- **Dimensions:** 176(L) x 116(W) x 63(D)mm